

SI.No.	Parameter	Data type	Address	OM 1300	OM 1310	ALPHA+ A	ALPHA+ V	ALPHA+ 3A	ALPHA+ 3V	ALPHA+Hz	ALPHA+ RPM	ALPHA+3VAF	ALPHA+ ADC	ALPHA+ VDC
1	PF Avg(inst)	float	40117		✓									
2	PF R phase	float	40119		✓									
3	PF Y phase	float	40121		✓									
4	PF B phase	float	40123		✓									
5	VLL average	float	40133	✓	✓		✓		✓			✓	✓	
6	Vry phase	float	40135	✓	✓				✓			✓		
7	Vyb phase	float	40137	✓	✓				✓			✓		
8	Vbr phase	float	40139	✓	✓				✓			✓		
9	VLN average	float	40141	✓	✓				✓			✓		
10	V R phase	float	40143	✓	✓				✓			✓		
11	V Y phase	float	40145	✓	✓				✓			✓		
12	V B phase	float	40147	✓	✓				✓			✓		
13	Current average	float	40149	✓	✓	✓		✓				✓	✓	
14	Current R phase	float	40151	✓	✓	✓		✓				✓	✓	
15	Current Y phase	float	40153	✓	✓			✓				✓		
16	Current B phase	float	40155	✓	✓			✓				✓		
17	Frequency	float	40157	✓	✓				✓	✓	RPM	✓		
18	Neutral Current	float	40183		✓Apeak									
19	RPM	float	40215		✓						✓			