

SI No.	Parameter	Data Type	Address			
			Channel 1	Channel 2	Channel 3	Channel 4
1	Watts Total	float	4101	4201	4301	4401
	Watts R phase	float	4103	4203	4303	4403
3	Watts Y phase	float	4105	4205	4305	4405
	Watts B phase	float	4107	4207	4307	4407
5	PF Ave. (Inst.)	float	4109	4209	4309	4409
	PF R phase	float	4111	4211	4311	4411
7	PF Y phase	float	4113	4213	4313	4413
	PF B phase	float	4115	4215	4315	4415
9	VLL average	float	4117	4217	4317	4417
	Vry phase	float	4119	4219	4319	4419
11	Vyb phase	float	4121	4221	4321	4421
	Vbr phase	float	4123	4223	4323	4423
13	VLN average	float	4125	4225	4325	4425
	V R phase	float	4127	4227	4327	4427
15	V Y phase	float	4129	4229	4329	4429
	V B phase	float	4131	4231	4331	4431
17	Current Total	float	4133	4233	4333	4433
	Current R phase	float	4135	4235	4335	4435
19	Current Y phase	float	4137	4237	4337	4437
	Current B phase	float	4139	4239	4339	4439
21	Frequency	float	4141	4241	4341	4441
	Wh Received	float	4143	4243	4343	4443
23	R-Phase Wh	float	4145	4245	4345	4445
	Y-Phase Wh	float	4147	4247	4347	4447
25	B-Phase Wh	float	4149	4249	4349	4449
26	Load hour Recd	Unsigned Long	4151	4251	4351	4451
27	R-Phase load hour	Unsigned Long	4153	4253	4353	4453
28	Y-Phase load hour	Unsigned Long	4155	4255	4355	4455
29	B-Phase load hour	Unsigned Long	4157	4257	4357	4457
30	VAR total	float	4159	4259	4359	4459
31	VAR R phase	float	4161	4261	4361	4461
32	VAR Y phase	float	4163	4263	4363	4463
33	VAR B phase	float	4165	4265	4365	4465
34	VA total	float	4167	4267	4367	4467
35	VA R phase	float	4169	4269	4369	4469
36	VA Y phase	float	4171	4271	4371	4471
37	VA B phase	float	4173	4273	4373	4473
38	VAh total	float	4175	4275	4375	4475
39	VARh IND total	float	4177	4277	4377	4477
40	VARh CAP total	float	4179	4279	4379	4479
41	VAh R phase	float	4181	4281	4381	4481
42	VAh Y phase	float	4183	4283	4383	4483
43	VAh B phase	float	4185	4285	4385	4485
44	VARh IND R phase	float	4187	4287	4387	4487
45	VARh IND Y phase	float	4189	4289	4389	4489
46	VARh IND B phase	float	4191	4291	4391	4491
47	VARh CAP R phase	float	4193	4293	4393	4493
48	VARh CAP Y phase	float	4195	4295	4395	4495
49	VARh CAP B phase	float	4197	4297	4397	4497

*Optional (26-49)