

Sl. No.	Parameter	Data type	Address	LG+3121	LG+5120L	LG+3220	LG+5220
1	Watts Total	float	40101	✓	✓	✓	✓
2	Watts R phase	float	40103	✓	✓	✓	✓
3	Watts Y phase	float	40105	✓	✓	✓	✓
4	Watts B phase	float	40107	✓	✓	✓	✓
5	PF Avg(inst)	float	40117	✓	✓	✓	✓
6	PF R phase	float	40119	✓	✓	✓	✓
7	PF Y phase	float	40121	✓	✓	✓	✓
8	PF B phase	float	40123	✓	✓	✓	✓
9	VA total	float	40125		✓		
10	VA R phase	float	40127		✓		
11	VA Y phase	float	40129		✓		
12	VA B phase	float	40131		✓		
13	VLL average	float	40133		✓		✓
14	Vry phase	float	40135		✓		✓
15	Vyb phase	float	40137		✓		✓
16	Vbr phase	float	40139		✓		✓
17	VLN average	float	40141		✓		✓
18	V R phase	float	40143		✓		✓
19	V Y phase	float	40145		✓		✓
20	V B phase	float	40147		✓		✓
21	Current average	float	40149		✓		✓
22	Current R phase	float	40151		✓		✓
23	Current Y phase	float	40153		✓		✓
24	Current B phase	float	40155		✓		✓
25	Frequency	float	40157		✓		✓
26	Wh received	float	40159	✓ Prog	✓ Prog	✓ Prog	✓ Prog
27	VAh received	float	40161	✓ Prog	✓ Prog	✓ Prog	✓ Prog
28	Wh Delivered	float	40167	✓ Prog	✓ Prog	✓ Prog	✓ Prog
29	VAh Delivered	float	40169	✓ Prog	✓ Prog	✓ Prog	✓ Prog
30	Load Hours Received	Unsigned long	40217	✓	✓	✓	✓
31	Load Hours Delivered	Unsigned long	40219	✓	✓	✓	✓