

Sl. No.	Parameter	Data type	Address	MPS 8000	MPU 5110
1	Watts Total	float	40101	✓	✓
2	Watts R phase	float	40103	✓	✓
3	Watts Y phase	float	40105	✓	✓
4	Watts B phase	float	40107	✓	✓
5	VAR Total	float	40109	✓	
6	VAR R phase	float	40111	✓	
7	VAR Y phase	float	40113	✓	
8	VAR B phase	float	40115	✓	
9	PF Avg(inst)	float	40117	✓	✓
10	PF R phase	float	40119	✓	✓
11	PF Y phase	float	40121	✓	✓
12	PF B phase	float	40123	✓	✓
13	VA total	float	40125	✓	✓
14	VA R phase	float	40127	✓	✓
15	VA Y phase	float	40129	✓	✓
16	VA B phase	float	40131	✓	✓
17	VLL average	float	40133	✓	✓
18	Vry phase	float	40135	✓	✓
19	Vyb phase	float	40137	✓	✓
20	Vbr phase	float	40139	✓	✓
21	VLN average	float	40141	✓	✓
22	V R phase	float	40143	✓	✓
23	V Y phase	float	40145	✓	✓
24	V B phase	float	40147	✓	✓
25	Current average	float	40149	✓	✓
26	Current R phase	float	40151	✓	✓
27	Current Y phase	float	40153	✓	✓
28	Current B phase	float	40155	✓	✓
29	Frequency	float	40157	✓	✓
30	Wh received	float	40159	✓	✓ Prog
31	VAh received	float	40161	✓	✓ Prog
32	VARh Ind. Received	float	40163	✓	
33	VARh Cap. Received	float	40165	✓	
34	PF Average Received	float	40175	✓	
35	Amps hours Received	float	40177	✓	
36	Neutral Current	float	40183	✓	
37	Voltage R Harmonics	float	40185	✓	

Sl. No.	Parameter	Data type	Address	MPS 8000	MPU 5110
38	Voltage Y Harmonics	float	40187	✓	
39	Voltage B Harmonics	float	40189	✓	
40	Current R Harmonics	float	40191	✓	
41	Current Y Harmonics	float	40193	✓	
42	Current B Harmonics	float	40195	✓	
43	RPM	float	40215	✓	
44	Load Hours Received	Unsigned long	40217	✓	✓
45	No of interruptions	Unsigned long	40221	✓	
46	ON hours ( in seconds)	Unsigned long	40231	✓	
47	Voltage R phase angle	float	40233	✓	
48	Voltage Y phase angle	float	40235	✓	
49	Voltage B phase angle	float	40237	✓	
50	Current R phase angle	float	40239	✓	
51	Current Y phase angle	float	40241	✓	
52	Current B phase angle	float	40243	✓	
53	Voltage Unbal R Phase	float	40259	✓	
54	Voltage Unbal Y Phase	float	40261	✓	
55	Voltage Unbal B Phase	float	40263	✓	
56	Current Unbal R Phase	float	40265	✓	
57	Current Unbal Y Phase	float	40267	✓	
58	Current Unbal B Phase	float	40269	✓	